

JR3 Multi-Axis Force-Torque Sensor Technical Specifications (SI Units)

Sensor Model: Mechanical Load Rating:	67M25A3 100N	67M25A3 200N
Diameter (mm)	67	67
Thickness (mm)	25	25
Material	AL 2024	AL 2024
Weight (g)	175	175
Nominal Accuracy, all axes (% measuring range)	±1,0	±1,0
Operating Temp. Range, non-condensing (°C)	-40 to +65	-40 to +65
F_x, F_y		
Standard Measurement Range (N)	±100	±200
Digital Resolution (N)	0,025	0,050
Stiffness (N/m)	5,1e6	13e6
Single-axis Overload (N)	470	930
Multi-axis Overload Coefficient, a (N)	470	930
Multi-axis Overload Coefficient, b (N)	600	1200
Multi-axis Overload Coefficient, c (N)	490	970
F_z		
Standard Measurement Range (N)	±200	±400
Digital Resolution (N)	0,050	0,100
Stiffness (N/m)	51e6	130e6
Single-axis Overload (N)	1900	3870
Multi-axis Overload Coefficient, d (N)	1900	3870
M_x, M_y		
Standard Measurement Range (Nm)	±6,3	±12
Digital Resolution (Nm)	0,0016	0,0032
Stiffness (Nm/rad)	21 200	53 000
Single-axis Overload (Nm)	28	58
Multi-axis Overload Coefficient, e (Nm)	40	79
Multi-axis Overload Coefficient, f (Nm)	105	215
Multi-axis Overload Coefficient, g (Nm)	28	58
M_z		
Standard Measurement Range (Nm)	±6,3	±12
Digital Resolution (Nm)	0,0016	0,0032
Stiffness (Nm/rad)	5360	15 000
Single-axis Overload (Nm)	21	48
Multi-axis Overload Coefficient, h (Nm)	22	48

Standard Measurement Range

- This is the range of loads that each sensor model is ideally suited to measure. Factory adjustments to internal electronics allow custom measurement ranges to meet application-specific needs.

Bolt Patterns

- The 67M25A3 and 67M25S3 (300N only) sensors are available standard with the ISO 9409-1 Ø40mm bolt pattern.
- Alternate and custom bolt patterns are also available.

Multi-axis Overloads

- Insert your applied loads and the coefficients from the above table into the equations below to determine safe loading:

$$F_x/a + F_y/a + F_z/d + M_x/e + M_y/e + M_z/h \leq 1$$
 and

$$F_x/b + F_y/c + F_z/d + M_x/f + M_y/g + M_z/h \leq 1$$
 and

$$F_x/c + F_y/b + F_z/d + M_x/g + M_y/f + M_z/h \leq 1$$
 All 3 equations must be satisfied to avoid damage.
- If additional overload capability is desired we recommend using a higher-rated sensor with electronically lowered measuring ranges.